
Sensor-switched LED floodlight

# XLED home 2 black EAN 4007841 033071





#### **Function description**

Top seller. Now even better. XLED home 2 sensor-switched outdoor floodlight for even more safety and security. Fully swivelling LED panel in classy stainless-steel look. For the most exacting of demands on design and maximum lighting convenience. 1184 Im at a power consumption of only 14,8 W. Swivelling precision IR sensor (horizontally: 180°, vertically: 90°). 140° angle of coverage, 14 m reach. High thermal conductivity magnesium composite cooling system (HCMC).

#### **Technical specifications**

Dimensions (L x W x H)	194 x 180 x 161 mm
Mains power supply	230 – 240 V / 50 – 60 Hz
Mounting height max.	4,00 m
Sensor Technology	passive infrared
Output	14,8 W
Interconnection	Yes
Type of interconnection	Sensor/slave
Interconnection, number	maximum of 10 floodlights
Luminous flux	1184 lm
Colour temperature	4000 K
Colour variation LED	SDCM3
Colour Rendering Index CRI	80-89
With lamp	Yes, STEINEL LED system
Lamp	LED cannot be replaced
LED life expectancy (max. °C)	50000 h
Drop in luminous flux in accordan with LM80	<sup>ICE</sup> L70B10
LED cooling system	HCMC (High Conductive Magnesium Composite)


With motion detector	Yes
Detection angle	140 °
Sneak-by guard	Yes
Capability of masking out individual segments	Yes
Reach, radial	r = 3 m (11 m <sup>2</sup> )
Photo-cell controller	Yes
Time setting	8 s – 35 Min.
Impact resistance	IK03
IP-rating	IP44
Protection class	II
Housing material	HCMC
Cover material	Plastic, opal
Manufacturer's Warranty	5 years
PU1, net weight	0,565 kg
Version	black
PU1, EAN	4007841033071

Sensor-switched LED floodlight

XLED home 2 black EAN 4007841 033071




# **Detection Zone**



Mögliche Montagehöhe: 1,80 m – 4,00 m Orange: radial Schwarz: tangential

#### **Light Distribution Curve**




14	,8 W
Ye	s, STEINEL LED system

LED cannot be replaced 1184 lm 4000 K

80-89 50000 h

HCMC (High Conductive Magnesium Composite)

# **Dimension Drawing**




- +

- 180 -

Master circuit diagram

H

161 —




Sensor-switched LED floodlight

XLED home 2 black EAN 4007841 033071



# Master/master interconnection circuit diagram



## Master/slave interconnection circuit diagram

